

Thank you for purchasing our device. Before installing, using or repairing the device, please read this manual carefully and pay attention to the safety warnings and instructions. This will ensure not only the protection of persons, but also the long service life of the device.

## TECHNICAL PARAMETERS

Product code	WM-30WS-T
Voltage	AC 220V - 240V, 50Hz
Power and light output	30W and 3900lm (100%) 20W and 2600lm (66%)
Colour rendering	3000K/4000K/5000K
Sensor detection distance	max. 10 m (up to 24°C)
Lighting time setting	5s - 10min
Sensor light sensitivity setting	3-2000 LUX
IP rating	IP6
Operating temperature	-20°C to +50°C
Dimensions	158 x 190 x 30 mm

Note: Power (W) and colour temperature (K) can be switched by unscrewing the cover and using the switch on the back of the device.

## WARNING

- This product is Class I and must be earthed.
- Always switch off the power supply using the switch on the device before installation.
- If the device is damaged, do not use it.
- After installation or maintenance, make sure that all seals are intact and functional.
- Do not touch the device during operation or shortly after use, as there is a risk of burns.
- Keep the device away from flammable materials.
- Do not wash or immerse the device.
- Only look at the light from a safe distance, as it may damage your eyesight.
- The device must only be installed by a qualified electrician.

## INSTALLATION

Before installation, disconnect the power supply from the mains and switch off the switch.

1. Select a suitable location for installing this device.
2. Unscrew the waterproof connector on the bottom of the device.
3. Connect the power cable and observe the marked wiring!
4. Do not forget to tighten all parts of the waterproof clamp.
5. Unscrew the screw on the back of the device to reveal the power (W) and colour temperature (K) controls.
6. Use the switches to select the lighting setting.
7. Insert the dowels into the pre-drilled holes and screw the bracket in place.
8. Switch on the power supply.

## SENSOR SETTINGS

Set the individual parameters on the rear of the sensor:

**TIME:** Turn to set the lighting time from sensor activation.

**LUX:** Set the switching sensitivity depending on the ambient light conditions.

**SENS:** Set the switching sensitivity to motion.

The light source of this luminaire is not replaceable. At the end of its service life, the entire luminaire must be replaced and disposed of at a designated location. This product contains a light source that cannot be removed for verification due to its design, and therefore the entire product is considered a light source. The power cord cannot be replaced. If it is damaged, the device must not be used.

The product is covered by a CE declaration of conformity in accordance with applicable regulations.

Available on request from the manufacturer: [info@solight.cz](mailto:info@solight.cz), or downloadable from [www.solight.cz/en](http://www.solight.cz/en).

