

Thank you for purchasing our device. Before installing, using or repairing the device, please read this manual carefully and pay attention to the safety warnings and instructions. This will ensure not only the protection of persons, but also the long service life of the device.

TECHNICAL PARAMETERS

Product code	WM-20W-T	WM-50W-T	WM-100W-T	WM-150W-T
Voltage	AC 220V - 240V, 50Hz	AC 220V - 240V, 50Hz	AC 220V - 240V, 50Hz	AC 220V - 240V, 50Hz
Power and light output	20W and 2600lm (100%) 10W and 1300lm (50%)	50W and 6500lm (100%) 30W and 3900lm (60%)	100W and 14000lm (100%) 75W and 10500lm (75%) 50W and 7000lm (50%)	150W and 21000lm (100%) 100W and 14000lm (67%) 70 W and 9800 lm (47%)
Colour rendering	3000K/4000K/5000K	3000K/4000K/5000K	3000K/4000K/5000K	3000K/4000K/5000K
IP rating	IP65	IP65	IP65	IP65
Operating temperature	-20°C to +50°C	-20°C to +50°C	-20°C to +50°C	-20°C to +50°C
Dimensions	128 x 96 x 30 mm	192 x 146 x 30 mm	280 x 207 x 30 mm	320 x 230 x 30 mm

Note: Power (W) and colour temperature (K) can be switched by unscrewing the cover and using the switch on the back of the device.

WARNING

- This product is Class I and must be earthed.
- Always switch off the power supply using the switch on the device before installation.
- If the device is damaged, do not use it.
- After installation or maintenance, make sure that all seals are intact and functional.
- Do not touch the device during operation or shortly after use, as there is a risk of burns.
- Keep the device away from flammable materials.
- Do not wash or immerse the device.
- Only look at the light from a safe distance, as it may damage your eyesight.
- Installation must only be carried out by a qualified electrician.

INSTALLATION

Before installation, switch off the power supply from the mains and the switch.

1. Select a suitable location for installing this device.
2. Unscrew the waterproof connector on the bottom of the device.
3. Connect the power cable and ensure that the wiring is correct!
4. Do not forget to tighten all parts of the waterproof clamp.
5. Unscrew the screw on the back of the device to reveal the power (W) and colour temperature (K) controls.
6. Use the switches to select the lighting setting.
7. Insert the dowels into the pre-drilled holes and screw the bracket in place.
8. Switch on the power supply.

The light source of this luminaire is not replaceable. At the end of its service life, the entire luminaire must be replaced and disposed of at a designated location. This product contains a light source that cannot be removed for verification due to its design, and therefore the entire product is considered a light source. The power cord cannot be replaced. If it is damaged, the device must not be used.

The product is covered by a CE declaration of conformity in accordance with applicable regulations.
Available on request from the manufacturer: info@solight.cz, or downloadable from www.solight.cz/en.

