

Dear customer, thank you for purchasing our product. Please read the following instructions carefully and follow them to ensure safe and satisfactory use. This will prevent misuse or damage. Avoid improper handling of this device and always follow the principles of using electrical appliances. Keep the instructions for use in a safe place.

TECHNICAL PARAMETERS

Power consumption	10W/m*
IP rating	IP20
Colour temperature	RGB – can be switched using a remote control

For maximum service life and performance, we recommend installing the strips in aluminium profiles

* With increasing LED strip length, the luminous flux (lm) and power consumption (W) per metre decrease. For a 5 m strip, the values per metre decrease by approximately 25% compared to the values listed

INSTALLATION

1. Clean the surface to which you are going to attach the LED strip.
2. Adjust the length of the strip as needed. Shorten the strip at the marked points. The remaining parts can be reused. Connectors must be purchased to reconnect the strip.
3. The LED strip is equipped with adhesive tape on the underside. Peel off the protective layer and stick the strip in place.
4. Finally, plug the power adapter into a socket.

NOTICE

- For maximum service life and performance, the strips must be installed on an aluminium base (in aluminium profiles) to prevent overheating.
- The strip is equipped with a power adapter with a switch: AC 230V / DC 12V, 2500mA.
- As the length of the LED strip increases, the luminous flux (lm) and power consumption (W) per metre decrease. For a 5m strip, the values per metre decrease by approximately 25% compared to the values listed.
- The strip can be shortened as needed (the remaining parts can be reused).
- Avoid placing the light fixture near objects that are sources of heat or moisture.
- Do not stare directly at the lit light for a long time, as this may cause discomfort or damage to your eyesight.
- Do not expose the light to the outdoors, direct rain, or submerge it in water. The light is intended for indoor use.
- Wipe the light fixture regularly with a dry or damp cloth only when it is disconnected from the mains.

REMOTE CONTROL



1. Speed setting +/- / Brightness +/-
2. Static colour
3. Flashing mode
4. STROBE mode
5. Transition mode 1
6. Transition mode 2

The light source of this luminaire is non-replaceable. At the end of its service life, the entire luminaire must be replaced and disposed of at a designated location. This product contains a light source that cannot be removed for verification due to its design, and therefore the entire product is considered a light source. The power cord cannot be replaced. If it is damaged, the device must no longer be used.

CE IP20